

## EUROLITE LED SCY-3 Beam effect

Bright LED architectural spot with IR remote control

Art. No.: 51918668

GTIN: 4026397534405



**The article is no longer in our assortment.**

### Features:

- Equipped with 3 x 10 W QCL (quadcolor LED) in red, green, blue and white
- Supports QuickDMX - the wireless DMX-system from Eurolite
- Built-in phantom fed socket for QuickDMX receiver (see accessories)
- UpLight for fan and beam effects on walls; e.g. on fairs and exhibitions, galas, events, shows, in clubs etc.
- 4, 6, 9 or 12 DMX channels selectable
- TILT angle manually adjustable
- Controllable via EUROLITE IR-7 remote control; included in delivery
- DMX-controlled operation or stand-alone operation with Master/Slave function
- Functions: static colors, stepless RGBW color changing, color presets, preset color temperatures, internal programs, dimmer, strobe effect with variable speed, sound-control
- Dimmer speed (step response) adjustable
- Adjustable microphone sensitivity
- Power supply input and output and DMX input and output oppositely attached to the unit for easier wiring
- Addressing via control panel with LED display
- Flat housing form requires minimal space when rigging
- Switch-mode power supply for operation between 100 and 240 Volts
- Ready for connection via included power cable with safety power plug
- Feed-through output allows to power up to 8 devices
- DMX control via any standard DMX controller
- Control via IR remote control; stand-alone; DMX
- Preprogrammed in Light 'J'
- Flicker-free

### Package contents

- 1 x remote control

### Logistic

EAN / GTIN: 4026397534405

Weight: 3,00 kg

Length: 0.34 m

Width: 0.16 m

Height: 0.28 m

## Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
IP classification:	IP20
Lamp type:	LED lamp
Control:	IR remote control; stand-alone; DMX
Preprogrammed in:	Light J
Projection:	Flicker-free
Housing color:	Black
Dimensions:	Width: 27,3 cm Depth: 8 cm Height: 21,2 cm
Weight:	2,70 kg
Remote control	
Battery:	1 x Button cell 3.0 V CR2025 lithium manganese built-in
Power consumption:	25 W
DMX channels:	4/6/9/12
DMX connection:	3-pin XLR
QuickDMX connection:	5-pin XLR
Sound-control:	via built-in microphone
LED type:	10 W QCL
LED number:	3
Remote control:	
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting