eurolite®

EUROLITE ERX-4 DMX Switch Pack

4-channel switch pack, up to 5 A load per channel, control with relay

Art. No.: 70064210 GTIN: 4026397521788









List price: 141.61 €

incl. 19% VAT.

Features:

- Relay allows for controlling luminaires with electronic transformers (e.g. LED effects)
- 4 controllable channels
- LED indicator per channel
- 5 A load per channel
- Rugged metal housing
- Control via stand-alone; DMX
- For application areas such as: Clubs/dancing school; party room; theater; restaurants, bars and hotels
- Silent operation
- Package contents
- 1 x device, 1 x user manual

Technical specifications:

Power supply:	230 V AC, 50 Hz
Output power:	Max. 3680 W
	Max. 1150 W per channal
Output current:	Max. 16 A
Power connection:	Fixed power supply cord with safety plug
Power output:	4 x safety contact (F), hinged lid mounting version
Power output fuse per channel:	5 x 20 mm, T 6,3 A fuse replaceable
DMX channels:	4

Logistic

EAN / GTIN: 4026397521788 Weight: 2,60 kg Length: 0.34 m Width: 0.28 m Heigth: 0.14 m

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.

DMX input:	3-pin XLR (M) mounting version
DMX output:	3-pin XLR (F) mounting version
Control:	Stand-alone; DMX
Control channels:	4
Color:	Black
Dimensions:	Width: 30 cm
	Depth: 19 cm
	Height: 8,5 cm
Weight:	2,51 kg
Noise classification:	Class 0 (no noise at all)