

EUROLITE DMX Stage Control 136 controller

Versatile DMX controller

Art. No.: 70064535

GTIN: 4026397220353



Description:

Let's bring them together! On this DMX Stage control, parcans and movinglights can be operated simultaneously. It fits best in little clubs, hotel dicotheques or on manageable live events, where only a few programs are needed. The controller is easy to use and is seperated in 128 movinglight- and 8 parcan-channels.

Logistic

EAN / GTIN: 4026397220353

Weight: 3,75 kg

Length: 0.58 m

Width: 0.32 m

Heigth: 0.16 m

Features:

- 136 control channels DMX out and MIDI in
- 8 channel-faders with LED
- Fade Time fader with LED for adjusting the step time
- Master-fader with LED for adjusting the total output level
- Speed-fader for adjusting the program-speed
- Audio-fader with LED for adjusting the music sensitivity
- CF memory card for programs
- LCD display
- External power supply
- 6.3 mm jack connection for footswitch (scene steps)
- 0/10 V-output via one 5-pin DIN-socket for fog machine
- Simultaneous and independent control of scanner and parcan section
- Dimmer: Manual control of the channels via sliders
- Full On: all channels can be switched on together
- Blackout-function
- Program speed adjustable via speed-fader or Tap Sync-button
- Sound-control via external signal or integrated microphone
- Sound to light via RCA socket
- Rack mounting plates included

- Rack installation with 4 units
- Scanner Section:
 - 128 control channels for 8 scanners with up to 16 DMX channels
 - 12 pages with up to 8 scenes can be programmed
 - 8 chasers each with up to 99 steps
 - Programmable speed and fade time
 - Patch possibility
 - Joystick with fine mode and 4 step buttons
- Dimmer Section:
 - 8 dim fader channels and 1 master fader
 - 12 pages with up to 6 scenes can be programmed
 - 6 chasers each with 99 steps
 - Speed, tap-sync und audio fader
 - Step function
 - Standby and full-on
- Can transmit up to 136 DMX channels
- Control via DMX
- Desktop console housing

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	6.00 W
DMX channels:	Output 136
Control:	DMX
Color:	Black
Housing design:	Desktop console housing
Dimensions:	Width: 21.5 cm Depth: 6.4 cm Height: 28 cm
Weight:	3.30 kg
	via 12 V DC, 600 mA power unit included in the delivery
Number of control channels:	136
Sound-control:	via built-in microphone or via audio-input
Audio-input:	Jack
Audio-sensitivity:	0.1-1 V
DMX512 output:	3-pin XLR connector with polarity selector
Free chasers:	8 for scanner section and 6 for dimmer section
Dimensions (L x W x H):	483 x 180 x 93 mm
	Rack installation with 4 u
Minimum mounting depth:	100 mm

Scope of delivery: