

OMNITRONIC MPZ-180 PA mixing amplifier

4 zone PA mixing amplifier switchable zones, 180 W RMS

Art. No.: 80709720

GTIN: 4026397176353



The article is no longer in our assortment.

Features:

- Comfortable control of your PA speakers via 4-zone technology
- 4 PA zone outputs, independently switchable on the front panel
- Master PA output (70 V and 100 V)
- Output for low-impedance speakers (4-16 ohms)
- 3 microphone inputs (6.3 mm jack, unbal.) with separate level controls
- Microphone input 3 with adjustable priority circuit
- 3 line inputs (stereo RCA) with separate level controls
- 1 line output (stereo RCA)
- Chime, switchable
- Treble and bass control for the output signal
- 7-fold LED level display
- Master control for the output signal
- Fan-cooled
- Protection circuits with LED indication: over current, short circuit, turn-on delay
- Rack installation

Logistic

EAN / GTIN: 4026397176353

Weight: 12,45 kg

Length: 0.56 m

Width: 0.48 m

Height: 0.20 m

Technical specifications:

Power supply: 230 V AC, 50 Hz

Output power: 180 W RMS

Frequency range: 80 - 16000 Hz

Zone output: 4 switchable zones

Dimensions: Width: 48,3 cm

Depth: 38,5 cm
Height: 8,9 cm

Output power:	180 W RMS
Output type:	70 V, 100 V or 4-16 ohms
Output current:	2.5 A/70 V, 1.8 A/100 V
Mic input:	5 mV, 600 ohms
Line input:	300 mV, 10 kohms
Output connectors:	Screw connectors, terminal block
Distortion:	0.5 % (1 kHz)
S/N ratio:	
Aux:	85 dB
Mic:	75 dB
Dimensions:	483 x 385 x 92 mm
Weight:	12 kg
