

## OMNITRONIC EMX-1 4-channel club mixer

PRO 4-channel DJ mixer

Réf. : 10006766

GTIN: 4026397355611



### Caractéristiques:

- 4 channels with gain control, cue button and super-smooth channel faders
- 1 DJ microphone channel with talkover selector and 2-band equalizer
- Pre-fader listening to the stereo input channels via adjustable headphones output
- Replaceable crossfader for crossfading between input channels with assignment switches
- Master channel with super-smooth fader, graphic 5-band equalizer and 10-digit stereo LED level meter
- Record output, independent of the master
- Inputs: 5 x line (stereo RCA), 2 x phono/line (stereo RCA), switchable; 1 x microphone (6.3 mm jack), 1 x microphone (XLR) and headphones (6.3 mm jack)
- Outputs: master and record (both stereo RCA)
- Operation via supplied power unit
- Rack installation, 4 U
- (19") 48,3 cm installation en rack

### Logistique

EAN / GTIN: 4026397355611

Poids: 4,60 kg

Longueur: 0.53 m

Largeur: 0.31 m

Hauteur: 0.15 m

### Données techniques:

|                                   |                                                               |
|-----------------------------------|---------------------------------------------------------------|
| Puissance totale de raccordement: | 30,00 W                                                       |
| Plage de fréquence:               | 20 - 20000 Hz                                                 |
| Conception du boîtier:            | (19") 48,3 cm installation en rack                            |
| Dimension:                        | Largeur : 48,3 cm<br>Profondeur : 17,9 cm<br>Hauteur : 8,9 cm |

|                               |                                   |
|-------------------------------|-----------------------------------|
| Poids:                        | 3,42 kg                           |
| Power supply:                 | 230 V AC, 50 Hz,                  |
|                               | via supplied power unit           |
| Inputs:                       |                                   |
| DJ microphone (front):        | 3-pin XLR                         |
| MIC 2 (rear):                 | 6.3 mm jack (1/4") (bal.)         |
| Impedance:                    | 1 kohms                           |
| Minimum input voltage:        | 1.5 mV RMS                        |
| LINE 1-4:                     | stereo RCA                        |
| Impedance:                    | 27 kohms                          |
| Minimum input voltage:        | 150 mV RMS                        |
| PHONO 1.2:                    | stereo RCA                        |
| Impedance:                    | 47 kohms                          |
| Minimum input voltage:        | 3 mV RMS                          |
| Outputs:                      |                                   |
| MASTER:                       | stereo RCA                        |
| Impedance:                    | 400 ohms                          |
| Output voltage:               | 1 V RMS/ 0 dB                     |
| REC:                          | stereo RCA                        |
| Impedance:                    | 5 kohms                           |
| Output voltage:               | 225 mV RMS                        |
| Headphones output:            | 6.3 mm stereo jack (min. 16 ohms) |
| Tone control (DJ microphone): |                                   |
| 1 x High:                     | -12 dB to +12 dB/ 10 kHz, ±1 dB   |
| 1 x Low:                      | -12 dB to +12 dB/ 100 Hz, ±1 dB   |
| Tone control (MASTER):        |                                   |
| 7-band equalizer:             | ±15 dB/ 60 Hz, 100 Hz, 1 kHz,     |
|                               | 6 kHz, 15 kHz, ±1 dB              |
| S/N ratio:                    | >80 dB                            |
| Distortion:                   | 0.02%                             |
| Dimensions (WxHxD):           | 483 x 179 x 102 mm (19", 4 U)     |

## Contenu de la livraison: