

## EM-760A Entertainment mixer

Mixeur d'installation à 6+1 canaux avec amplificateur de puissance à 2 x 2 canaux

Réf. : 10007127

GTIN: 4026397219883



## EM-760A Entertainment mixer

Mixeur d'installation à 6+1 canaux avec amplificateur de puissance à 2 x 2 canaux

Réf. : 10007127

GTIN: 4026397219883

### Caractéristiques:

---

- Amplifier with 4 x 150 W power/ 8 ohms
- 6 input channels with gain control, 3-way equalizer and super smooth dual-rail channel faders
- 1 separate microphone channel with level control, 2-way equalizer and talkover button
- Pre-fader listening (CUE) to the stereo input channels via adjustable headphone output
- Color illuminated rotary controls and rubber buttons
- 2 adjustable master outputs with 10-digit stereo LED level meter
- 1 adjustable booth output with mono/stereo selector switch
- 2 record outputs, independent of the master channels
- Inputs: 9 x line (stereo RCA), 3 x line/phono (stereo RCA), switchable; 6 x microphone (6.3 mm jack), 1 x microphone (XLR/6.3 mm jack) and headphones (6.3 mm jack)
- Outputs: 2 x master (optionally 3-pin XLR or stereo RCA), 1 x booth (stereo RCA) and 2 x record (stereo RCA)
- Speaker connection via lockable Speaker plugs or banana/screw combination