

## OMNITRONIC MRS-1402USB Recording Mixer

Compact audio mixer with 14 inputs and USB interface

Réf. : 10040273

GTIN: 4026397513905



**L'article n'est plus disponible.**

### Caractéristiques:

- Built-in USB audio interface allows recordings and playback of digital audio files with a computer (PC and Mac)
- Full duplex USB port: simultaneous recording and playback possible
- 4 mono input channels with gain control, 3-way EQ, Low Cut and pan control
- 4 stereo input channels with 3-way EQ, level switch and balance control
- Adjustable stereo aux send output
- Tape input and output
- Separate main mix and control room outputs
- Headphones output
- +48 V phantom power, can be switched centrally
- Precise 4-digit stereo LED level display
- Operation via supplied power unit
- Rugged, compact metal housing

### Logistique

EAN / GTIN: 4026397513905

Poids: 2,97 kg

Longueur: 0.43 m

Largeur: 0.30 m

Hauteur: 0.08 m

### Données techniques:

Alimentation électrique: 230 V AC, 50 Hz

Puissance totale de raccordement: 28,00 W

Branchement électrique: Alimentation électrique via Fiche creuse (M)  
version encastrable Câble d'alimentation et bloc d'alimentation (inclus dans la livraison)

Plage de fréquence: 20 - 20000 Hz

Port USB: USB 2.0, Typ B

Dimension:	Largeur : 27 cm Profondeur : 21,5 cm Hauteur : 7,2 cm
Poids:	2,72 kg
Inputs/sensitivity:	
Mic, mono	0.5 mV, XLR bal.
Line In, mono	1 mV, 6.3 mm jack bal.
Line In, stereo	10 mV, 6.3 mm jack L/R
Tape In	100 mV, RCA L/R
Outputs/level:	
Main Out:	650 mV, 6.3 mm jack L/R unbal.
Control Room	2 V max. 6.3 mm jack L/R unbal.
Aux Send:	2 V, 6.3 mm jack unbal.
Tape Out	2 V, RCA L/R
Headphones	2 V, 6.3 mm jack unbal.
Distortion:	0.05 %
S/N ratio:	>74 dB
Tone control/channel:	
Treble:	±15 dB at 12 kHz
Middle:	±15 dB at 2.5 kHz
Bass:	±15 dB at 80 Hz
Phantom power:	+48 V