

## OMNITRONIC ZD-1120 Zone Distributor

Practical distributor

Réf. : 10304102

GTIN: 4026397303650



## L'article n'est plus disponible.

### Description:

Make 12 out of 1. That's true to the motto of our OMNITRONIC ZD-1120 zone distributor. You have one input signal (RCA/XLR) which, thanks to the ZD-1120, can now be sent to 12 different outputs (RCA). And at every output the level control and the mono switch can be set individually - LED displays alleviate the metering.

Where can you use a zone distributor? Just imagine a wellness center for example. In facilities like that you can normally find many different rooms. Now if you want music to be played in the rooms with different volumes and you don't want to purchase one player for each room, then our ZD-1120 can offer the solution. At last, it distributes the input signal to 12 zones, or rooms in this case. But the ZD-1120 is not only designed for wellness centers of course. It's up to you to decide, where and how you want to use it. And be sure, it will be a great help.

### Caractéristiques:

- Extends every mixer with additional outputs
- 1 stereo XLR input
- 12 stereo zone outputs (RCA)
- Each zone with level control and mono switch
- LED display of signal input and mono/stereo mode
- Rack installation with 1 U
- (19") 48,3 cm installation en rack 1 HE

### Données techniques:

Alimentation électrique: 230 V AC, 50 Hz

### Logistique

EAN / GTIN: 4026397303650

Poids: 3,05 kg

Longueur: 0.53 m

Largeur: 0.27 m

Hauteur: 0.09 m

Puissance totale de raccordement:	7,00 W
Branchement électrique:	Alimentation électrique via Appareils froids (M) version encastrable Câble d'alimentation à prise contact de protection (inclus dans la livraison)
Rapport signal/bruit:	>100 dB
Distorsion harmonique:	<0,02 % avec 1 kHz
Impédance:	Entrée: 47 kOhm Sortie: 50 Ohm
Niveau max.:	Sortie: +1 V
Conception du boîtier:	(19") 48,3 cm installation en rack 1 HE
Dimension:	Largeur : 48,3 cm Profondeur : 15 cm Hauteur : 4,45 cm
Poids:	2,80 kg