

## OMNITRONIC LH-115 Personal Monitor Mixer

Monitor mixer for studio and stage applications

Réf. : 10355115

GTIN: 4026397318555



## L'article n'est plus disponible.

### Description:

The LH-115 provides the opportunity to perfectly record your voice recordings: Take your microphone signal and send it to the LH-115. With one or two headphones you now can now tap the signal and send it, unaltered, to your computer. From there again you can send another signal, background music for example, back to the mixer. Now you can speak sort of on the music and with the level control you are able to easily set the volume of the microphone signal. On your monitor signal you can thus hear the mix the way you prefer it for recording. And due to its small size, it's the ideal partner on the way.

### Logistique

EAN / GTIN: 4026397318555

Poids: 0,73 kg

Longueur: 0.23 m

Largeur: 0.13 m

Hauteur: 0.08 m

### Caractéristiques:

- Connects a microphone and a further audio source for monitoring
- 1 microphone input via balanced XLR connector with level control
- 1 feed-through output (XLR, bal.)
- 1 aux input via 6.3 mm jack with level control
- 2 headphone outputs via 6.3 mm jacks
- Operation via supplied power unit

### Données techniques:

Alimentation électrique:	12 V 150 mA
Puissance totale de raccordement:	2,00 W
Branchement électrique:	Alimentation électrique via Fiche creuse (M) version encastrable Câble d'alimentation et bloc d'alimentation (inclus dans la livraison)

Plage de fréquence:	50 - 20000 Hz
Rapport signal/bruit:	>90 dB
Impédance:	Sortie: 10 Ohm
Gain:	Microphone 50 dB Line 20 dB
Dimension:	Largeur : 11,3 cm Profondeur : 4 cm Hauteur : 9 cm
Poids:	700 g