

OMNITRONIC DJP-300 Digital amp, 2x150W

Digital monitor amplifier

Réf. : 10451600

GTIN: 4026397246414



L'article n'est plus disponible.

Caractéristiques:

- Extremely efficient due to SMPS technology
- Advantages in low weight and little space due to switch mode power supply instead of large and heavy transformers
- Switch mode power supply
- High efficiency, operation via safety power outlet
- Extremely wide frequency range covers the whole bandwidth
- Power supply with softstart
- High impulse stability
- Stable metal housing, light and compact
- Extremely compact fully digital power amplifier, e.g. for medium-sized monitor speakers or studio applications

Logistique

EAN / GTIN: 4026397246414

Poids: 3,10 kg

Longueur: 0.34 m

Largeur: 0.27 m

Hauteur: 0.11 m

Données techniques:

Alimentation électrique: 115/230 V CA, 50/60 Hz

Puissance totale de raccordement: 350,00 W

Puissance de sortie: 80 W RMS (8 Ohm)

Plage de fréquence: 5 - 100 Hz

Dimension:
Largeur : 21 cm
Profondeur : 30 cm
Hauteur : 4,5 cm

Poids: 2,40 kg

Power output (RMS):

| | |
|----------------------------|---|
| Stereo 4 ohms | 2 x 150 W |
| Stereo 8 ohms | 2 x 80 W |
| Signal-to-noise ratio: | >110 dB |
| Total harmonic distortion: | 0.01 % |
| Input connectors: | 4 x RCA |
| Output connectors: | 2 x pole terminal |
| Controls: | Power switch, input selector, Gain/Balance/Treble/Bass control |
| Construction: | Steel chassis |