

OMNITRONIC TM-1000 MK2 Pocket transmitter

Émetteur de poche à émetteur multifréquence PLL

Réf. : 13055511

GTIN: 4026397415353



L'article n'est plus disponible.

Description:

For the rough stage use
The TM-1000 pocket transmitter comes in a rugged metal housing and withstands every rough stage use. A robust case with foam padding is included for save transport.

Caractéristiques:

- Multifrequency pocket transmitter with UHF pilot tone technology (PLL)
- Matches receiver DR-1000 MK2
- Suitable for lavalier microphones or headsets with mini XLR plug
- Operation in the low-interference UHF band (740-764 MHz)
- 192 carrier frequencies switchable in 125 kHz steps (40 frequencies per MHz)
- Transmitting power 10 mW, operation range 100 meters
- Multichannel operation with up to 16 pocket transmitters possible
- LCD for battery status and frequency
- Sensitivity adjustable
- Lock function avoids undesired changes by users, also accidental shutdown
- Operation via 2 x 1.5 V mignon battery (type AA), not included
- Can also be used for direct guitar pickup (via optional adapter cable)
- License required in Germany

Logistique

EAN / GTIN: 4026397415353

Poids: 0,87 kg

Longueur: 0,36 m

Largeur: 0,17 m

Hauteur: 0,08 m

Données techniques:

Batterie: 2 x 1,5 V AA Mignon LR06 alcaline au manganèse ci-joint

Bande de fréquences:	UHF
Dimension:	Largeur : 19,6 cm Profondeur : 10,6 cm Hauteur : 7,8 cm
Poids:	640 g
Antenna:	Built-in
Carrier frequency:	UHF 740-764 MHz
Switching bandwidth:	24 MHz
No. of frequencies:	192
Frequency steps:	125 kHz
Modulation:	FM
Frequency stability:	±0.005 %
AF response:	40-18000 Hz
RF power output:	10 mW
Coverage:	100 m (with line-of-sight)
Current consumption:	100 mA
Connection:	3-pin mini XLR