

OMNITRONIC AD-500 Antenna Distributor Set

Répartiteur d'antenne

Réf. : 13063032
GTIN: 4026397438321



L'article n'est plus disponible.

Caractéristiques:

- Active antenna distributor for operating up to four UHF receivers on one pair of multi-antennas
- Improves the interference safety and enlarges the range
- Replaces the respective antennas and PSUs of the individual receivers
- Up to five antenna distributors AD-500 can be connected among each other for use of 16 microphones in total
- Directional antennas made of durable glass/copper with 1.5 cm thread (5/8") for stands
- Low-voltage outputs for supplying four UHF receivers, incl. matching connection cables
- Use in the entire UHF frequency range (600 - 900 MHz)
- All antenna connections via BNC jacks
- Rack installation with 1 unit
- Rugged steel housing
- Incl. padded transport case, with aluminum profile frames

Logistique

EAN / GTIN: 4026397438321
Poids: 5,80 kg
Longueur: 0.55 m
Largeur: 0.40 m
Hauteur: 0.14 m

Données techniques:

| | |
|-----------------------------------|--|
| Type: | Antenne et distributeur |
| Alimentation électrique: | 100-240 V CA, 50/60 Hz |
| Puissance totale de raccordement: | 40,00 W |
| Dimension: | Largeur : 48,3 cm Profondeur : 21 cm Hauteur : 4,45 cm |
| Poids: | 5,77 kg |

| | |
|-------------------------|----------------------------|
| Frequency range: | 600-900 MHz |
| Impedance: | 50 ohms |
| Antenna connectors: | 2 x BNC |
| Receiver outputs: | 8 x BNC |
| Low-voltage outputs: | 4 x 12 V DC |
| Dimensions distributor: | 482 x 210 x 44 mm |
| | Rack installation with 1 U |
| Dimensions antennas: | 315 x 336 mm |