

OMNITRONIC WMR-1M MK1 UHF Receiver, mono

Système de transmission sans fil audio mono, 823-832 MHz

Réf. : 13072331

GTIN: 4026397550573



L'article n'est plus disponible.

Caractéristiques:

- Wireless audio transmission system with UHF PLL technology
- For wireless transmission of audio line and microphone signals (mono) with one transmitter and one or more receivers
- Duplex gap 823-832 MHz
- Parallel use of up to 4 transmitters possible
- Operating range up to 50 m
- Audio line output and earphone connection via 3.5 mm mono jack
- 16 channels selectable
- Volume level control
- RF reception indicator
- LED battery indicator
- Robust metal fixing clip
- Power supply via 2 x 1.2 V NiMH rech. battery AA size (not included)
- Micro USB charging port
- License-free in large parts of the EU

Logistique

EAN / GTIN: 4026397550573

Poids: 0,28 kg

Longueur: 0.21 m

Largeur: 0.09 m

Hauteur: 0.07 m

Données techniques:

Batterie: 2 x 1,5 V AA Mignon R06 zinc-carbone ci-joint

Dimension: Largeur : 6,5 cm
Profondeur : 2,7 cm
Hauteur : 11 cm

Type: 16-channel PLL audio receiver

| | |
|----------------------|--------------------------------|
| Frequency range: | 823-832 MHz |
| Range: | min. 50 m |
| Modulation: | FM |
| Frequency stability: | 10 ppm |
| Pilot frequency: | 32,768 kHz |
| S/N ratio: | >80 dB |
| Line/earphone input: | 3.5 mm mono jack |
| Max. output voltage: | 500 mV |
| Dimensions: | 110 x 65 x 27 mm (w/o antenna) |
| Weight: | 93 g (w/o batteries) |