

OMNITRONIC TM-105 Transmitter set W05

Émetteur de poche multifréquence pour WAMS-05

Réf. : 13075003

GTIN: 4026397282610



L'article n'est plus disponible.

Description:

The set includes a pocket transmitter with PLL multifrequency transmitter and a headset microphone which serves for wireless transmission of speech and vocals to the receiving unit RM-105 of the PA system W.A.M.S.-05. The transmitter operates in the range of 863.100 - 864.900 MHz. The frequency range is divided into 16 channels, which can be selected as desired. The unit is tuned to the frequencies of the receiver module.

Logistique

EAN / GTIN: 4026397282610

Poids: 0,23 kg

Longueur: 0.17 m

Largeur: 0.13 m

Hauteur: 0.06 m

Caractéristiques:

- Set includes pocket transmitter and headset microphone
- Transmitter as UHF PLL system, suitable for W.A.M.S.-05 system
- Suitable for optional lavalier microphone LS-105
- Operation in the low-interference UHF-band (863.1-864.9 MHz) with 16 frequencies selectable
- LCD for channel, frequency and battery capacity
- Sensitivity adjustable in 3 steps
- Transmitting power 10 mW
- For 2 x 1.5 V mignon batteries or 2 x 1.2 V rechargeable batteries (type AA) (not included)
- With charging contacts, suitable for optional charging station TM-105
- Connection via 3.5 mm mini jack
- License-free and approved in the EU

Données techniques:

Batterie: 2 x Mignon (AA) (non incluse dans la livraison)

Bande de fréquences: UHF

Dimension:	Largeur : 8,8 cm Profondeur : 6,4 cm Hauteur : 2,6 cm
Poids:	170 g
Modulation:	FM
Carrier frequency:	UHF 863.000-865.000 MHz
Microphone type:	Condenser with cardioid pattern
RF power output:	10 mW
Coverage:	50-70 m (with line-of-sight)
Frequency range:	50-18000 Hz (± 3 dB)
Frequency stability:	± 0.005 %
Rechargeable battery life:	approx. 11 hours
Audio input:	3.5 mm stereo mini jack