

EUROLITE LED TSL-100 Scan COB

Bright LED-scanner

Réf. : 51786120

GTIN: 4026397380422



L'article n'est plus disponible.

Description:

LED as good as never before!

LEDs continue to be on the rise. Eurolite's new TSL-100 scanner therefore sets an impressive example. Because it realizes the brightness of a 250 Watt halogen scanner with absolute brilliant colors. What is so special about this scanner is the fact, that the LED (in this case a white 20W LED) replaces the light source. A clear difference compared to the many rivals which use the diodes for producing the patterns. Despite the low power consumption, the TSL-100 creates an impressive brightness - and effects, such as gobos or color changes are generated just in the same way normal scanner do. And this marks the big difference to the existing LED scanners. They can just be compared to small light effect with 100 Watt as they illustrate their patterns via a matrix of diodes. The EUROLITE LED Scan TSL-100 clearly shows, what LEDs are able to achieve.

Caractéristiques:

- Equipped with a 20 W COB LED
- Long LED life
- Comparable to the light output of a 250 W halogen lamp
- DMX-controlled operation or stand-alone operation with Master/Slave function (up to 4 slaves)
- 14 motion macros can be called up via DMX controller
- Sound-controlled via built-in microphone
- Microphone-sensitivity adjustable via rotary-control
- Fuzzy sound control: program continues automatically during periods without music or bass-beat
- 8 brilliant, dichroic colors plus white
- Rainbow effect with adjustable speed
- Gobo-wheel with 8 static gobos plus open
- With gobo-shake function

Logistique

EAN / GTIN: 4026397380422

Poids: 6,60 kg

Longueur: 0.48 m

Largeur: 0.28 m

Hauteur: 0.29 m

- Strobe effect with 1-18 flashes per second
- Strobe effect with adjustable speed
- Random strobe effect
- Manual focus
- Dimmer
- Small and portable
- Lightbeam with 13° radiation angle
- Control board with 4-digit display for adjusting the DMX-starting address, Pan/Tilt-Reverse
- 6.3 mm jack socket for remote control
- Blackout, gobos, colors and Auto/Manual Mode applicable in Stand Alone mode via optional EUROLITE RC-1 remote control
- Advantages of LED technology: long life, low power consumption, minimal heat emission, defacto maintenance free with brilliant light radiation
- DMX control via every standard DMX controller
- 1 LED puissante
- Gobos
- Effet gobo
- L'appareil est refroidi par ventilateur
- Commandé via stand-alone; DMX; Commande de la musique via Microphone
- Déjà préprogrammé pour %: Light´J; Light Captain

Données techniques:

Alimentation électrique:	230 V AC, 50 Hz
Puissance totale de raccordement:	50 W
Type de protection:	IP20
Type de lampe:	Lampe LED
LED:	1
Fréquence du flash:	1 - 18 Hz
Équipement:	Gobos
Canaux DMX:	8
Refroidissement:	Ventilateur
Commande:	Stand-alone; DMX; Commande de la musique via Microphone
Préprogrammé dans:	Light´J; Light Captain
Angle de départ (1/2 pic):	13°
Couleur du boîtier:	Noir
Dimension:	Largeur : 20,5 cm Profondeur : 39 cm Hauteur : 30 cm
Poids:	5,55 kg
DMX channels:	8
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
Flash-rate:	18 Hz
Color-wheel:	8 colors and open
Static gobo-wheel:	8 gobos and open
LED type:	Array 20 W
LED number:	1
Dimensions (L x W x H):	390 x 205 x 300 mm
Spécifications juridiques	

Produit spécial:	Non destiné à l'éclairage de la pièce dans les ménages
Utilisation:	Éclairage pour effets de spectacle