

FUTURELIGHT DMH Quad-150 LED Moving Head

High performance LED Moving Head with 150 W COB LED in RGBW colors

Réf. : 51842100

GTIN: 4026397503142



L'article n'est plus disponible.

Caractéristiques:

- Equipped with a 150 W COB LED in RGBW colors
- 18, 20 or 23 DMX channels selectable
- With integrated wireless receiver for WDMX operation (Wireless Solution - made in Sweden)
- Effect wheel with rotating 3-facet prism
- Macro function for rotating gobos/rotating prism combinations
- Stepless RGBW color changing
- Gobo wheel 1 with 7 rotating gobos plus open
- All gobos can be interchanged
- Slot-in gobo system for exchanging gobos without tools
- With gobo shake function
- Gobo wheel 2 with 7 static gobos plus open
- Exact positioning via 16 bit PAN/TILT movement resolution, gobo indexing, focus, iris
- Dimmer
- Motorized focus
- Frost filter
- Steplessly adjustable iris
- Strobe effect with adjustable speed
- Random strobe effect
- Automatic position correction
- PAN angle switchable between 630°, 540° - 90° offset or 540°
- Switch-mode power supply, automatic power supply adaption between 100 and 240 Volts without power selector
- Sound-controlled via built-in microphone
- ESDC function (Easy Service Data Check) with battery-buffered control board for operation time readouts etc.

Logistique

EAN / GTIN: 4026397503142

Poids: 23,40 kg

Longueur: 0.69 m

Largeur: 0.48 m

Hauteur: 0.45 m

- Control board with graphic LCD display and foil-keyboard for adjusting the DMX-starting address, PAN/TILT reverse, reset
- DMX-controlled operation or stand-alone operation with Master/Slave function
- 56 preprogrammed scenes in Program Run for stand-alone operation
- Number of scenes in Program Run can be changed individually
- The scenes in Program Run can be modified via the Control Board or via an external controller and loaded into the memory
- 7 built-in programs can be called up via DMX controller
- Software upload by optional FUTURELIGHT ULB-1 upload box via DMX link
- DMX control via every standard DMX controller
- Commandé via Commande de la musique via Microphone; RDM
- Déjà préprogrammé pour %: Light Captain
- Vous trouverez de plus amples informations sur ce produit dans la rubrique « Téléchargements » de la fiche technique

Données techniques:

Alimentation électrique:	100-240 V CA, 50/60 Hz
Puissance totale de raccordement:	240 W
Mouvement de basculement max. TILT:	265° Positionnement
Mouvement de pivotement max. PAN:	630° Positionnement
Fréquence du flash:	1 - 13 Hz
Gobos:	Diamètre externe 27mm Diamètre de l'image 22mm
Canaux DMX:	18
Commande:	Commande de la musique via Microphone; RDM
Préprogrammé dans:	Light Captain
Angle de départ (1/2 pic):	17°
Couleur:	Noir
Dimension:	Largeur : 36,2 cm Profondeur : 39,3 cm Hauteur : 49,6 cm
Poids:	20,05 kg
DMX channels:	18/20/23
DMX connection:	5-pin and 3-pin XLR
Sound-control:	via built-in microphone
Wireless signal transmission:	2.4 GHz (ISM)
Flash-rate:	13 Hz
LED type:	Array Cluster 150 W, RGBW
LED number:	1
Beam angle:	17°
Rotating gobo-wheel:	7 gobos and open
Static gobo-wheel:	7 gobos and open
Outside diameter of the gobos:	27 mm
Image diameter of the gobos:	22 mm
Maximum PAN-movement:	630°
Maximum TILT-movement:	265°
Dimensions (L x W x H):	362 x 393 x 496 mm
Spécifications juridiques	

Produit spécial: Non destiné à l'éclairage de la pièce dans les ménages

Utilisation: Éclairage pour effets de spectacle
