

## EUROLITE FD-512 DMX Dimmer Panel

Handy DMX controller for 512 channels

Réf. : 70063815

GTIN: 4026397512229



**L'article n'est plus disponible.**

### Caractéristiques:

- Compact DMX controller for convenient operation of light effect units with DMX512 interface (e.g. spotlights and dimmers)
- Simply connect and operate, requires no extensive programming
- 512 control channels
- 8 channel faders for adjusting the DMX values in 64 groups
- Internal memory for 1 scene
- Flash push-button with LED
- Flash time adjustable (0.1s-10min)
- Blackout push-button with LED
- 2 x 16-digit LCD screen
- 3-pin and 5-pin XLR connectors
- Mounting frame for rack installation available as accessory
- Power supply via included power unit
- Peut envoyer jusqu'à 512 canaux DMX
- Commandé via DMX
- Boîtier du pupitre

### Logistique

EAN / GTIN: 4026397512229

Poids: 1,50 kg

Longueur: 0.40 m

Largeur: 0.23 m

Hauteur: 0.12 m

### Données techniques:

Alimentation électrique: 100-240 V CA, 50/60 Hz

Puissance totale de raccordement: 1,00 W

Type de protection: IP20

Canaux DMX: Sortie 512

Commande:	DMX
Couleur du boîtier:	Noir
Couleur:	Noir
Conception du boîtier:	Boîtier du pupitre
Dimension:	Largeur : 17,8 cm Profondeur : 29,2 cm Hauteur : 5,9 cm
Poids:	1,25 kg
	via included power unit
Number of control channels:	512
DMX512 output:	3-pin and 5-pin XLR connector
Dimensions (L x W x H):	292 x 178 x 59 mm