

OMNITRONIC ZD-1120 Zone Distributor

Practical distributor

Art.n.: 10304102

GTIN: 4026397303650



Descrizione :

Make 12 out of 1. That's true to the motto of our OMNITRONIC ZD-1120 zone distributor. You have one input signal (RCA/XLR) which, thanks to the ZD-1120, can now be sent to 12 different outputs (RCA). And at every output the level control and the mono switch can be set individually - LED displays alleviate the metering.

Where can you use a zone distributor? Just imagine a wellness center for example. In facilities like that you can normally find many different rooms. Now if you want music to be played in the rooms with different volumes and you don't want to purchase one player for each room, then our ZD-1120 can offer the solution. At last, it distributes the input signal to 12 zones, or rooms in this case. But the ZD-1120 is not only designed for wellness centers of course. It's up to you to decide, where and how you want to use it. And be sure, it will be a great help.

Features :

- Extends every mixer with additional outputs
- 1 stereo XLR input
- 12 stereo zone outputs (RCA)
- Each zone with level control and mono switch
- LED display of signal input and mono/stereo mode
- Rack installation with 1 U
- Montaggio su rack (19") 48,3 cm 1 U

Dati tecnici :

Alimentazione elettrica: 230 V AC, 50 Hz

Logistica

EAN / GTIN: 4026397303650

Peso : 3,05 kg

Lunghezza : 0.53 m

Larghezza : 0.27 m

Altezza : 0.09 m

| | |
|------------------------------|--|
| Potenza totale installata: | 7,00 W |
| Allacciamento elettrico: | Alimentazione dell'energia elettrica tramite dispositivi a freddo (M) versione da incasso cavo di alimentazione con spina di protezione (in dotazione) |
| Rapporto segnale-rumore: | >100 dB |
| Distorsione armonica totale: | <0,02 % a 1 kHz |
| Impedenza: | Ingresso: 47 kOhm Uscita: 50 Ohm |
| Livello massimo: | Uscita: +1 V |
| Struttura della custodia: | Montaggio su rack (19") 48,3 cm 1 U |
| Misure: | Larghezza: 48,3 cm Profondità: 15 cm Altezza: 4,45 cm |
| Peso: | 2,80 kg |

Contenuto della confezione:
