

## OMNITRONIC PNM-6 Nearfield Monitor

Active speaker with 6.5" woofer, 2.5" driver, 40 W RMS

Art.n.: 11036456

GTIN: 4026397513929



### Features :

- Active nearfield monitor for DJs and producers
- 2-way bass-reflex system with biamp amplifier
- Separate controls for volume, high and low frequencies
- For home studio and multimedia use
- 6.3 mm jack and 3-pin XLR input for connection the audio source
- 17 cm bass-midrange speaker and 2.5 cm dome tweeter with wave guide
- Rugged black MDF cabinet

### Logistica

EAN / GTIN: 4026397513929

Peso : 8,10 kg

Lunghezza : 0.31 m

Larghezza : 0.29 m

Altezza : 0.43 m

### Dati tecnici :

Alimentazione elettrica:	115/230 V AC, 50/60 Hz
Potenza totale installata:	100,00 W
Allacciamento elettrico:	Alimentazione dell'energia elettrica tramite dispositivi a freddo (M) versione da incasso cavo di alimentazione con spina europea (in dotazione)
Capacità di carico:	Programma: 80W Nominale: 40W RMS
Intervallo di frequenza:	45 - 20000 Hz
Sensibilità:	88 dB
Collegamenti:	Line via 1 x Jack da 6,3 mm (non sim.) Line via 1 x XLR a 3 poli

Altoparlante:	1 x 6.5" Woofer 1 x 2.5" tweeter a cupola
Tipo di altoparlante:	Monitor for studios
Misure:	Larghezza: 23 cm Profondità: 21 cm Altezza: 34 cm
Peso:	7,35 kg

**Contenuto della confezione:**

---