

## OMNITRONIC CP-30P PA Mixing Amplifier

Amplificatore PA con lettore audio, telecomando IR e Bluetooth, 30 W RMS

Art.n.: 80709601

GTIN: 4026397614763



**L'articolo non è più disponibile.**

### Descrizione :

Omnitronic CP series - very compact mixers for public address systems (100 V)  
The PA mono mixing amplifiers of the CP series have been specially designed for the use in 100 V PA systems. They supply an output power of 30, 60 or 120 watts. PA speakers with 70 V and 100 V audio transformers or low-impedance speakers can be connected.

It is possible to connect microphones and units with line level to the six inputs which can be mixed with each other. Microphone channel 1 is equipped with a priority function which reduces the volume of the other signal sources in case of an announcement. Additional input and output terminals connect a telephone system allowing you to make important announcements and to play music for people waiting to be answered.

The PA amplifiers are equipped with an audio player with Bluetooth receiver, USB port, SD card slot, and FM tuner with auto scan. An IR remote control is included for convenient control of the audio player.

### Logistica

EAN / GTIN: 4026397614763

Peso : 4,50 kg

Lunghezza : 0.40 m

Larghezza : 0.31 m

Altezza : 0.17 m

### Features :

- Compact PA mono mixing amplifier 1 x 30 W (CP-30P), 1 x 60 W (CP-60P), 1 x 120 W (CP-120P)
- Built-in audio player with Bluetooth receiver and IR remote control
- Stream music wirelessly from your mobile devices (e.g. smartphone, tablet) via Bluetooth
- SD card slot and USB input
- FM tuner with auto scan
- 3 microphone inputs with separate level controls
- Mic 1 (XLR) with phantom power and priority circuit
- Mic 2 and 3 (jack) switchable mic/line
- 2 aux inputs (RCA) with separate level controls

- 1 telephone input with priority and MOH circuit (Music on Hold) for telephone systems with audio output
- 1 line output (RCA)
- Treble and bass and master controls for the output signal
- 4-fold LED level display
- Protection circuits with LED indication: overload, short circuit, clip limiter, overheat
- Compact desktop console

#### **audioplayer**

- Controllabile via Bluetooth; Telecomando IR
- Bluetooth: Portata fino a 10m
- 2.4 GHz registrazione gratuita e gratuita in tutto il mondo

#### **Dotazione della fornitura**

- 1 x Amplificatori, 1 x Cavo di rete/Cavo di alimentazione, 1 x Antenna, 1 x telecomando, 1 x Manuale d'uso, 1 x dichiarazione di conformità

### **Dati tecnici :**

|                              |                                                                                                                                                                                                                                                                                                                                                                                               |
|------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Alimentazione elettrica:     | 230 V AC, 50 Hz<br>O<br>24V DC                                                                                                                                                                                                                                                                                                                                                                |
| Potenza totale installata:   | 60 W                                                                                                                                                                                                                                                                                                                                                                                          |
| Potenza in uscita:           | 30 W RMS                                                                                                                                                                                                                                                                                                                                                                                      |
| Allacciamento elettrico:     | Alimentazione dell'energia elettrica tramite dispositivi a freddo (M) versione da incasso cavo di alimentazione con spina di protezione (in dotazione)<br><br>Alimentazione dell'energia elettrica tramite terminale a vite possibile                                                                                                                                                         |
| Intervallo di frequenza:     | 60 - 15000 Hz                                                                                                                                                                                                                                                                                                                                                                                 |
| Rapporto segnale-rumore:     | >75 dB microfono<br>>85 dB line                                                                                                                                                                                                                                                                                                                                                               |
| Distorsione armonica totale: | <0,5 % a 1 kHz                                                                                                                                                                                                                                                                                                                                                                                |
| Impedenza:                   | 4 Ohm; 8 Ohm; 16 Ohm; ELA tecnica 100 V                                                                                                                                                                                                                                                                                                                                                       |
| Commutazione:                | Class D                                                                                                                                                                                                                                                                                                                                                                                       |
| Collegamenti:                | Antenna via 1 x F connector (F) mounting version<br>Ingresso: microfono via 1 x XLR a 3 poli<br>Ingresso: mic/line via 2 x Presa jack (stereo) da 6,3 mm versione da incasso<br>Ingresso: line via 2 x RCA stereo<br>Ingresso: TEL via terminale a vite 0,1 V<br>Uscita: line via 1 x RCA stereo 0,774 V<br>Uscita: Altoparlante via terminale a vite<br>Uscita: MOH via terminale a vite 1 V |
| Equalizzatore:               | Master: 1 x regolatore a 2 bande Mono                                                                                                                                                                                                                                                                                                                                                         |
| Materiale:                   | Metallo                                                                                                                                                                                                                                                                                                                                                                                       |
| Misure:                      | Larghezza: 32 cm<br>Profondità: 23,8 cm<br>Altezza: 9,3 cm                                                                                                                                                                                                                                                                                                                                    |
| Peso:                        | 3,9 kg                                                                                                                                                                                                                                                                                                                                                                                        |
| Attivazione:                 | Bluetooth; Telecomando IR                                                                                                                                                                                                                                                                                                                                                                     |
| Audioplayer:                 | USB + SD + Bluetooth + radio FM                                                                                                                                                                                                                                                                                                                                                               |
| Massima:                     | Bluetooth: fino a 10m                                                                                                                                                                                                                                                                                                                                                                         |
| Banda di frequenza:          | 2.4 GHz                                                                                                                                                                                                                                                                                                                                                                                       |
| Formato musicale:            | MP3                                                                                                                                                                                                                                                                                                                                                                                           |

|                          |                                                         |
|--------------------------|---------------------------------------------------------|
| Alimentazione elettrica: | 3V DC                                                   |
| Allacciamento elettrico: | Pila/Batteria ricaricabile montato                      |
| Pila:                    | 1 x pila a bottone 3,0 V CR2025 litio-manganese montato |