

EUROLITE VSD-104 Video distributor 1in4

4-way AV distributing amplifier

Art.n.: 81013010

GTIN: 4026397279917



Features :

- Distribute audio, composite video and s-video television signals from a single AV source to multiple television monitors
- Daisy-chain several units for larger displays with equal picture quality and save the expense of additional AV receivers
- Typical applications are information systems in shopping centers, schools, hotels, railway stations, airports etc.
- Integrated amplifier for lossless signal transmission
- Signal transmission up to 50 meters
- Additional Aux In for connecting a music source
- 12 V power supply via power unit included in the delivery

Logistica

EAN / GTIN: 4026397279917

Peso : 0,90 kg

Lunghezza : 0.31 m

Larghezza : 0.13 m

Altezza : 0.06 m

Dati tecnici :

Alimentazione elettrica: 100-240 V AC, 50/60 Hz

Potenza totale installata: 6,00 W

Intervallo di frequenza: 20 - 100 Hz

Rapporto segnale-rumore: >100 dB

Distorsione armonica totale: <0,05 % a 1 kHz

Misure: Larghezza: 24,2 cm

Profondità: 12,8 cm

Altezza: 5 cm

Peso:	0,77 kg
<hr/>	
Video:	
<hr/>	
1 x input:	1 Vpp/ 75 ohms, composite RCA
<hr/>	
4 x outputs:	1 Vpp/ 75 ohms, composite RCA
<hr/>	
Gain:	2 V, 1 V (terminated)/ 75 ohms
<hr/>	
Return loss:	>18 dB
<hr/>	
Video bandwidth:	>100 MHz
<hr/>	
Audio:	
<hr/>	
2 x inputs:	22 kohms, stereo RCA and 3.5 mm jack (1/8")
<hr/>	
4 x outputs:	1 kohms, stereo RCA
<hr/>	
Gain:	nominal 0 dB
<hr/>	
Channel separation:	>75 dB
<hr/>	

Contenuto della confezione:
